

## Voltage and continuity testers

### PAN Allrounder 200AD

Easy to use like a voltage tester, versatile like a multimeter:  
Current/ voltage tester with LED + LCD display 1000V, 200A AC/DC  
True RMS

- Analog LED and backlit digital LCD display
- **Non contact voltage test (3 levels) (NCV)**
- Single pole phase test with acoustic indication
- **2-pole rotary field indication**
- Low voltages up to 24 V: green LEDs, dangerous voltages from 230 V: red LEDs
- **Vibrate alert and beep for confident feedback in any environment**
- **LED flashlight**
- Diode test
- Data Hold
- Auto power off

**Scope of delivery:** Operating manual, test leads, screw-contact sleeves for perfect contact in sockets



Technical Data	PAN Allrounder 200AD
DC voltage (V =)	0,1 V - 1500 V
AC voltage (V ~)	0,1 V - 1000 V
DC current (A =)	0,1 A - 200 A
AC current (A ~)	0,1 A - 200 A
Resistance (Ω)	1 Ω - 100 kΩ
Continuity test (•)))	< 40 Ω / < 500 kΩ
Frequency (Hz)	1 Hz - 800 Hz
Accuracy (%)	3 % - 5 %
Jaw opening ø	15 mm
Dimensions	197 x 63 x 38 mm
Weight (gross / net)	494 / 296 g
Required battery(s):	2 x 1,5V AAA
Measuring category (CAT)	CAT IV 600 V / CAT III 1000 V



### Autorisierter Distributor

**TVW Meßtechnik GmbH**  
Sammelweg 31  
32257 Bünde  
Fon: 05223 / 9277 - 0  
Fax: 05223 / 9277 - 40  
info@twwbuede.de  
www.twwbuede.de



PAN Allrounder 200AD Video DE:



PAN Allrounder 200AD Video EN:

